

DS-PM1-RT-HWE 868MHz Tri-X Wireless Receiver



Tri-X wireless receiver, compatible with AX Hybrid Pro control panel, used to expand wireless capability of the control panel. HIKVISION Tri-X detectors can be added to AX Hybrid Pro panel via this wireless receiver.

- 868MHz wireless receiver
- Wireless transmission distance up to 1700m
- Supports 32 wireless detectors, 4 wireless indoor sounders and 8 wireless outdoor sounders

▪ Specification



Software features	
Compatibility list	DS-PS1-I-WE DS-PS1-E-WE DS-PM1-O1L-WE DS-PM1-O1H-WE DS-PDP15P-EG2-WE DS-PDC15-EG2-WE DS-PDD12P-EG2-WE DS-PDMC-EG2-WE DS-PDMCS-EG2-WE DS-PDEB1-EG2-WE DS-PDEBP1-EG2-WE DS-PDWL-E-WE DS-PDPG12P-EG2-WE DS-PDMCK-EG2-WE DS-PDTPH-E-WE DS-PDCL12-EG2-WE DS-PDC10AM-EG2-WE DS-PDC10DM-EG2-WE
Hardware features	
Bus	1 Speed-X bus
Electrical characteristics	
Power supply	9 to 28 VDC, 1A
Power consumption	Maximum current 100 mA@12 VDC; Quiescent current 40 mA@12 VDC
Wireless transmission	
RF frequency	868 MHz
Wireless security	Frequency hopping 128 AES encryption
Display	
LED Indicator	1. Green: power/find me 2. Orange: alarm/fault
General	
Dimension(WxHxD)	110 mm × 155 mm × 32 mm
Shell material	Plastic
Weight	225 g
Operation temperature	-10°C to 40°C
Operation humidity	10% to 90%
Device management	
Alarm input	Up to 32 wireless detectors(portable emergency button is not included)
Wireless sounder	Up to 4 wireless indoor sounder, 8 wireless outdoor sounder

▪ Available Model

DS-PM1-RT-HWE

▪ **Accessory**

▪ **Included**

DS-PHA48-EP	DS-PHA64-LP
	

**The Detectors that DS-PM1-RT-HWE Supports*

Headquarters

No.555 Qianmo Road, Binjiang District,
Hangzhou 310051, China
T +86-571-8807-5998
www.hikvision.com



Follow us on social media to get the latest product and solution information.

