



Ranger Mini-R1 3MP

H.265 Wi-Fi Indoor Camera

With 3MP/2K live monitoring and 0~355° pan & -5~50° tilt features, Ranger Mini ensures every corner of your home completely covered. The Integrated-Bracket design allows easy installation either Ceiling Mounting or Wall Mounting. Human & Pet Detection quickly finds the targets in images and immediately sends a notification to you. Privacy Mode helps protect your personal privacy when you are home, and Smart Tracking function lets the camera follows moving objects when it detects motion.



H.265 3MP/2K

See more than 1080P



Integrated-Bracket

Easy installation either Ceiling Mounting or Wall Mounting



Wi-Fi Connection

IEEE802.11 b/g/n/ax (2.4GHz)



Human & Pet Detection

Quickly find human & pet targets in you home



Smart Tracking

Automatically tracks moving objects



Smart Color Night Vision

Support four-mode night vision for clear-as day clarity even in pitch dark



Two-way Talk

Real-time communicate with people at the camera



AOR Mode

Always-On-Record mode saves more storage space



Diversified Storage

Supports NVR, Cloud Storage or Micro SD card(up to 512GB)



Stay close with what you care

With Cloud service, you will have access to what you care as long as Internet is available. You can record daily or motion videos on Cloud and play back anytime anywhere.

Specifications

Camera

Image Sensor	1/3" Progressive CMOS
Max Resolution	3MP(2304×1296)
Night Vision	15m (49ft) Distance
Focal Length	3.6mm Fixed Lens
Field of View	91°(H), 47°(V), 107°(D)

Video & Audio

Video Compression	H.265/H.264
Video Frame Rate	Up to 20fps Frame Rate
Focal Length	8×Digital Zoom
Sound & Light	Built-in Mic&Speaker
	Built-in Spotlight

Network

Ethernet Port	1 x 100Mbps Ethernet Port
Imou App	IOS, Android Onvif

General

Power supply	DC 5V 1A Power Supply
Power Consumption	< 5W
Working Environment	-10°C~+45°C, Less Than 95%RH
Dimension(L×W×H)	95.0 × 96.0 × 109.2mm (3.74 × 3.78 × 4.30inch)
Weight	210g
Certification	CE

Auxiliary Interface

Micro SD Card	Up to 512GB
Built in Mic&Speaker	YES
Reset Button	YES

Notice Management

Smart Detection	Motion, Human, Pet, Abnormal Sound Alarm
-----------------	---

What's in the box

Camera × 1

Screw Package × 1

Quick Start Guide × 1

Installation Position Map × 1

Power Adapter × 1

Power Cable × 1